

wiringPi 编码	BCM 编 码	功能名	物理引脚 编码 BOARD		功能名	BCM 编 码	wiringPi 编码
		3. 3V	1	2	5V		
8	2	SDA. 1	3	4	5V		
9	3	SCL. 1	5	6	GND		
7	4	GPIO. 7	7	8	TXD	14	15
		GND	9	10	RXD	15	16
0	17	GPIO. 0	11	12	GPIO. 1	18	1
2	27	GPIO. 2	13	14	GND		
3	22	GPIO. 3	15	16	GPIO. 4	23	4
		3. 3V	17	18	GPIO. 5	24	5
12	10	MOSI	19	20	GND		
13	9	MISO	21	22	GPIO. 6	25	6
14	11	SCLK	23	24	CE0	8	10
		GND	25	26	CE1	7	11
30	0	SDA. 0	27	28	SCL. 0	1	31
21	5	GPIO. 21	29	30	GND		
22	6	GPIO. 22	31	32	GPIO. 26	12	26
23	13	GPIO. 23	33	34	GND		
24	19	GPIO. 24	35	36	GPIO. 27	16	27
25	26	GPIO. 25	37	38	GPIO. 28	20	28
		GND	39	40	GPIO. 29	21	29